

Console Messages ESY2140I - ESY2149I

Note: All console messages prefixed with ESY2 are valid for BS2000/OSD only.

Message	Explanation	Action
ESY2140I User :1: - throw away old request.	The reply processing for user :1: cannot continue. The ESY ID of the user has been changed while processing the current call. The reply is ignored.	No action required.
ESY2141I SERVER task :1: initialization.	The SERVER task notifies of starting the task initialization.	No action required.
ESY2142I SERVER task :1: ready.	The SERVER task notifies of successful task initialization.	No action required.
ESY2143I Invalid PRODUCT specified.	The operator command handler has detected an invalid value for command START or SHUTDOWN.	Please read the description of the operator command and use a correct value.
ESY2144I PRODUCT :1: posted to perform shutdown.	The SERVER task notifies of successful shutdown message delivery to product :1:.	No action required.
ESY2145E NATURAL-SUB-TASKING still active.	The Natural subtask handler cannot recreate the environment. The subsystem is still active.	Please contact Software AG.
ESY2146W NATURAL-SUB-TASK not started.	Start of Natural subtasking not permitted due to startup parameter setting. NATURAL-SUB-TASK functionality will not be available for this ESY run.	Check your startup parameters NATNUMSUB and JOBNATSUB.
ESY2147E Requested SERVER ID not available anymore.	The user session is linked to an abended server. The request cannot continued.	Please check the output files of the stopped or abended SERVER tasks for abnormal terminations.
ESY2148I No TRACE file written.	The TRACE environment is not established. Therefore, no file can be written containing available TRACE data.	No action required.
ESY2149I All buffer elements written to TRACE file.	All available TRACE data have been written to the assigned TRACE output file. The TRACE environment will be deleted now.	See section "How to create trace data in the Entire System Server" how to proceed with the output file in case of problems.